



# CFP2000 Result

Copyright ©1999-2005, Standard Performance Evaluation Corporation

## Supermicro

Motherboard X7DBR-8( 1.86GHz, Intel Xeon E5320 processor)

SPECfp2000 = 1938

SPECfp\_base2000 = 1935

SPEC license #01176 Tested by: Supermicro Test date: Oct-2006 Hardware Avail: Nov-2006 Software Avail: Mar-2006

Benchmark	Reference Time	Base Runtime	Base Ratio	Runtime	Ratio
168.wupwise	1600	59.7	2679	59.7	2678
171.swim	3100	128	2421	128	2421
172.mgrid	1800	150	1204	149	1204
173.applu	2100	140	1505	140	1505
177.mesa	1400	76.3	1835	76.3	1835
178.galgel	2900	64.1	4526	64.1	4525
179.art	2600	39.9	6515	39.9	6515
183.quake	1300	54.5	2385	53.0	2454
187.facerec	1900	94.7	2007	94.8	2005
188.amp	2200	162	1354	160	1371
189.lucas	2000	98.1	2039	98.1	2039
191.fma3d	2100	148	1418	148	1418
200.sixtrack	1100	147	748	149	738
301.apsi	2600	225	1155	225	1155

### Hardware

CPU: Intel Xeon E5320 processor ( 1.86 GHz,1066MHz bus)  
CPU MHz: 1860  
FPU: Integrated  
CPU(s) enabled: 4 cores, 1 chip, 4 cores/chip  
CPU(s) orderable: 1 chip  
Parallel: N/A  
Primary Cache: 32KBI + 32KBD on chip per core  
Secondary Cache: 8MB(I+D) on chip, per chip (4MB shared per 2 cores)  
L3 Cache: N/A  
Other Cache: N/A  
Memory: 8 X 2GB DDR2 ECC CL5 667MHz FBDIMM  
Disk Subsystem: 1 X Seagate Barracuda 120GB 7200 RPM  
Other Hardware: N/A

### Software

Operating System: Windows Server 2003 Enterprise Edition 32-bits w/ SP1  
Compiler: Intel C++ and Fortran Compiler 9.1 for 32-bit applications  
Build 20060323Z Package ID: W\_FC\_P\_9.1.020  
Microsoft Visual Studio 2005(for libraries)  
SmartHeap Library Version 8.0 from <http://www.microquill.com/>  
File System: NTFS  
System State: Default

## Notes/Tuning Information

```
+FDO: PASS1= -Qprof_gen PASS2=-Qprof_use
Base tuning for Fortran programs: -fast -Qansi_alias +FDO
Base tuning for 177.mesa: -fast +FDO shlw32M.lib
Base tuning for 179.art: -fast +FDO shlw32M.lib
Base tuning for 183.quake: -fast +FDO shlw32M.lib
Base tuning for 188.amp: -fast +FDO shlw32M.lib
Portability:
178.galgel: -FI /F32000000
Peak tuning:
168.wupwise: -fast -Qansi_alias +FDO
171.swim: -fast -Qansi_alias +FDO
172.mgrid: -fast -Qansi_alias +FDO
173.applu: basepeak=yes
177.mesa: basepeak=yes
178.galgel: -fast -Qansi_alias +FDO
179.art: basepeak=yes
183.quake: -QxP -Oa -Qrcd -Qipo +FDO shlw32M.lib
```



# CFP2000 Result

Copyright ©1999-2005, Standard Performance Evaluation Corporation

**Supermicro**

Motherboard X7DBR-8( 1.86GHz, Intel Xeon E5320 processor)

SPECfp2000 = 1938

SPECfp\_base2000 = 1935

SPEC license #01176 | Tested by: Supermicro | Test date: Oct-2006 | Hardware Avail: Nov-2006 | Software Avail: Mar-2006

## Notes/Tuning Information (Continued)

```
187.facerec: -fast -Qunroll11 -Qscalar_rep- +FDO
188.amp: -fast -Oa +FDO shlw32M.lib
189.lucas: -fast -Qprefetch- +FDO
191.fma3d: basepeak=yes
200.sixtrack: -Qipo -QxP +FDO
301.apsi: -fast +FDO
```

Tested systems can be used with SC816S-R700 case,  
To ensure system stability, a 500W (minimum) ATX power supply [4-pin (+12V), 8-pin (+12V) and 24-pin are required]  
Product description located as of <http://www.supermicro.com/products/motherboard/Xeon1333/5000P/X7DBR-8.cfm>  
The system bus runs at 1066 MHz